

## CGHV60075D5

## 75 W, 6.0 GHz, GaN HEMT Die

Cree's CGHV60075D5 is a gallium nitride (GaN) High Electron Mobility Transistor (HEMT). GaN has superior properties compared to silicon or gallium arsenide, including higher breakdown voltage, higher saturated electron drift velocity, and higher thermal conductivity. GaN HEMTs offer greater power density and wider bandwidths compared to Si and GaAs transistors.

### FEATURES

- 19 dB Typical Small Signal Gain at 4 GHz
- 17 dB Typical Small Signal Gain at 6 GHz
- 65% Typical Power Added Efficiency at 4 GHz
- 60% Typical Power Added Efficiency at 6 GHz
- 75 W Typical P<sub>SAT</sub>
- 50 V Operation
- High Breakdown Voltage
- Up to 6 GHz Operation

## APPLICATIONS

- 2-Way Private Radio
- Broaband Amplifiers
- Cellular Infrastructure
- Test Instrumentation
- Class A, AB, Linear amplifiers suitable for OFDM, W-CDMA, EDGE, CDMA waveforms



## **Packaging Information**

- Bare die are shipped on tape or in Gel-Pak® containers.
- · Non-adhesive tacky membrane immobilizes die during shipment.



## Absolute Maximum Ratings (not simultaneous)

Parameter	Symbol	Rating	Units	Conditions
Drain-source Voltage	V <sub>DSS</sub>	150	V <sub>DC</sub>	25°C
Gate-source Voltage	V <sub>GS</sub>	-10, +2	V <sub>DC</sub>	25°C
Storage Temperature	T <sub>stg</sub>	-65, +150	°C	
Operating Junction Temperature	TJ	225	°C	
Maximum Drain Current <sup>1</sup>	I <sub>MAX</sub>	6.3	А	25°C
Maximum Forward Gate Current	I <sub>GMAX</sub>	10	mA	25°C
Thermal Resistance, Junction to Case (packaged) <sup>2</sup>	$R_{_{ ext{ ext{ ext{ ext{ ext{ ext{ ext{ ext$	2.67	°C/W	85°C, 41.6W Dissipation
Thermal Resistance, Junction to Case (die only)	$R_{_{ ext{ ext{ ext{ ext{ ext{ ext{ ext{ ext$	1.66	°C/W	85°C, 41.6W Dissipation
Mounting Temperature	Τ <sub>s</sub>	320	°C	30 seconds

Note<sup>1</sup> Current limit for long term reliable operation.

Note<sup>2</sup> Eutectic die attach using 80/20 AuSn mounted to a 10 mil thick Cu15Mo85 carrier.

## Electrical Characteristics (Frequency = 6 GHz unless otherwise stated; $T_c = 25^{\circ}C$ )

Characteristics	Symbol	Min.	Тур.	Max.	Units	Conditions
DC Characteristics						
Gate Pinch-Off Voltage	V <sub>P</sub>	-3.8	-3.0	-2.3	V	$V_{_{DS}}$ = 10 V, I $_{_{D}}$ = 10 mA
Drain Current <sup>1</sup>	I <sub>DSS</sub>	8	10	-	А	$V_{_{\rm DS}}$ = 6 V, $V_{_{\rm GS}}$ = 2.0 V
Drain-Source Breakdown Voltage	V <sub>BD</sub>	150	-	-	V	$V_{gs}$ = -8 V, I <sub>D</sub> = 10 mA
On Resistance	R <sub>on</sub>	-	0.28	-	Ω	V <sub>DS</sub> = 0.1 V
Gate Forward Voltage	V <sub>G-ON</sub>	-	1.9	-	V	I <sub>GS</sub> = 10 mA
RF Characteristics						
Small Signal Gain	G <sub>ss</sub>	-	17	-	dB	$V_{_{DD}}$ = 50 V, I $_{_{DQ}}$ = 125 mA
Saturated Power Output <sup>2,3</sup>	P <sub>SAT</sub>	-	75	-	W	$V_{_{DD}}$ = 50 V, I $_{_{DQ}}$ = 125 mA
Drain Efficiency <sup>3</sup>	η	-	60	-	%	$V_{_{DD}}$ = 50 V, I $_{_{DQ}}$ = 125 mA, P $_{_{SAT}}$ = 75 W
Intermodulation Distortion	IM3	-	-30	-	dBc	$V_{_{DD}}$ = 50 V, I $_{_{DQ}}$ = 125 mA, P $_{_{OUT}}$ = 75 W PEP
Output Mismatch Stress	VSWR	-	-	10:1	Ψ	No damage at all phase angles, $V_{DD}$ = 50 V, $I_{DQ}$ = 125 mA $P_{OUT}$ = 75 W CW
Dynamic Characteristics						
Input Capacitance	C <sub>GS</sub>	-	9.51	-	pF	$V_{_{DS}}$ = 50 V, $V_{_{gs}}$ = -8 V, f = 1 MHz
Output Capacitance	C <sub>DS</sub>	-	3.6	-	pF	$V_{_{DS}}$ = 50 V, $V_{_{gs}}$ = -8 V, f = 1 MHz
Feedback Capacitance	$C_{GD}$	-	0.26	-	pF	$V_{_{DS}}$ = 50 V, $V_{_{gs}}$ = -8 V, f = 1 MHz

Notes:

<sup>1</sup> Scaled from PCM data

 $^2$   $P_{_{SAT}}$  is defined as  $I_{_{G}}$  = 1.0 mA.  $^3$  Drain Efficiency =  $P_{_{OUT}}/$   $P_{_{DC}}$ 

Copyright © 2014-2016 Cree, Inc. All rights reserved. The information in this document is subject to change without notice. Cree and the Cree logo are registered trademarks of Cree, Inc. Other trademarks, product and company names are the property of their respective owners and do not imply specific product and/or vendor endorsement, sponsorship or association.

Cree, Inc. 4600 Silicon Drive Durham, North Carolina, USA 27703 USA Tel: +1.919.313.5300 Fax: +1.919.869.2733 www.cree.com/rf



## **DIE Dimensions (units in microns)**



Overall die size  $3000 \times 820 (+0/-50)$  microns, die thickness 100 microns. All Gate and Drain pads must be wire bonded for electrical connection.

#### **Assembly Notes:**

- Recommended solder is AuSn (80/20) solder. Refer to Cree's website for the Eutectic Die Bond Procedure application note at www.cree.com/rf/document-library
- · Vacuum collet is the preferred method of pick-up.
- The backside of the die is the Source (ground) contact.
- Die back side gold plating is 5 microns thick minimum.
- Thermosonic ball or wedge bonding are the preferred connection methods.
- Gold wire must be used for connections.
- Use the die label (XX-YY) for correct orientation.

## **Electrostatic Discharge (ESD) Classifications**

Parameter	Symbol	Class	Test Methodology
Human Body Model	НВМ	1A (> 250 V)	JEDEC JESD22 A114-D
Charge Device Model	CDM	II (200 < 500 V)	JEDEC JESD22 C101-C

Copyright © 2014-2016 Cree, Inc. All rights reserved. The information in this document is subject to change without notice. Cree and the Cree logo are registered trademarks of Cree, Inc. Other trademarks, product and company names are the property of their respective owners and do not imply specific product and/or vendor endorsement, sponsorship or association.

Cree, Inc. 4600 Silicon Drive Durham, North Carolina, USA 27703 USA Tel: +1.919.313.5300 Fax: +1.919.869.2733 www.cree.com/rf



## **Typical Performance**



## **Product Ordering Information**

Order Number	Description	Unit of Measure	
CGHV60075D5	Bare Die	Each	

Copyright © 2014-2016 Cree, Inc. All rights reserved. The information in this document is subject to change without notice. Cree and the Cree logo are registered trademarks of Cree, Inc. Other trademarks, product and company names are the property of their respective owners and do not imply specific product and/or vendor endorsement, sponsorship or association.

Cree, Inc. 4600 Silicon Drive Durham, North Carolina, USA 27703 USA Tel: +1.919.313.5300 Fax: +1.919.869.2733 www.cree.com/rf

4 CGHV60075D5 Rev 1.1

## CREE ᆃ

## Typical Die S-Parameters (Small Signal, $V_{_{DS}}$ = 50 V, $I_{_{DQ}}$ = 125 mA, magnitude / angle)

Frequency	Mag S11	Ang S11	Mag S21	Ang S21	Mag S12	Ang S12	Mag S22	Ang S22
0.5	0.93309	-154.44	14.266	88.053	0.014402	-0.85181	0.35448	-119.95
0.6	0.93352	-158.34	11.838	83.444	0.01433	-5.2391	0.3779	-122.32
0.7	0.93452	-161.14	10.06	79.434	0.014195	-9.0268	0.40373	-124.1
0.8	0.93586	-163.24	8.7019	75.832	0.014019	-12.407	0.43075	-125.62
0.9	0.93743	-164.87	7.6297	72.531	0.013813	-15.485	0.45814	-127.01
1	0.93917	-166.17	6.761	69.468	0.013583	-18.326	0.48532	-128.36
1.1	0.94101	-167.24	6.0431	66.6	0.013336	-20.972	0.51193	-129.69
1.2	0.94292	-168.13	5.4398	63.9	0.013076	-23.449	0.5377	-131
1.3	0.94485	-168.89	4.926	61.348	0.012806	-25.779	0.56247	-132.31
1.4	0.9468	-169.55	4.4834	58.931	0.01253	-27.974	0.58611	-133.6
1.5	0.94872	-170.12	4.0987	56.635	0.012249	-30.047	0.60859	-134.86
1.6	0.95062	-170.64	3.7616	54.451	0.011966	-32.007	0.62986	-136.11
1.7	0.95247	-171.1	3.4641	52.373	0.011683	-33.861	0.64994	-137.32
1.8	0.95426	-171.51	3.2003	50.392	0.011401	-35.619	0.66885	-138.51
1.9	0.956	-171.89	2.9648	48.503	0.011122	-37.283	0.68662	-139.66
2	0.95767	-172.24	2.7539	46.699	0.010846	-38.863	0.70331	-140.77
2.1	0.95926	-172.56	2.5641	44.976	0.010574	-40.36	0.71895	-141.85
2.2	0.96079	-172.86	2.3927	43.33	0.010307	-41.781	0.73359	-142.89
2.3	0.96225	-173.14	2.2375	41.754	0.010045	-43.13	0.74731	-143.9
2.4	0.96364	-173.41	2.0963	40.247	0.0097893	-44.411	0.76014	-144.87
2.5	0.96496	-173.65	1.9677	38.802	0.0095396	-45.629	0.77216	-145.8
2.6	0.96621	-173.89	1.8502	37.416	0.0092961	-46.787	0.78341	-146.7
2.7	0.9674	-174.11	1.7425	36.087	0.0090588	-47.888	0.79393	-147.57
2.8	0.96853	-174.32	1.6437	34.811	0.0088279	-48.935	0.80379	-148.4
2.9	0.96959	-174.52	1.5528	33.584	0.0086033	-49.933	0.81303	-149.2
3	0.9706	-174.71	1.4689	32.404	0.0083851	-50.882	0.82169	-149.97
3.2	0.97246	-175.07	1.3198	30.177	0.0079668	-52.647	0.83741	-151.43
3.4	0.97412	-175.4	1.1918	28.105	0.0075724	-54.252	0.85128	-152.78
3.6	0.97561	-175.71	1.081	26.175	0.0072005	-55.712	0.86354	-154.03
3.8	0.97695	-175.99	0.98461	24.373	0.0068495	-57.041	0.87439	-155.19
4	0.97815	-176.26	0.90032	22.681	0.0065185	-58.254	0.88404	-156.27
4.2	0.97923	-176.5	0.82619	21.091	0.0062057	-59.361	0.89265	-157.28
4.4	0.9802	-176.74	0.76072	19.592	0.0059099	-60.372	0.90034	-158.21
4.6	0.98108	-176.96	0.70262	18.175	0.0056299	-61.295	0.90725	-159.09
4.8	0.98187	-177.17	0.65085	16.832	0.0053644	-62.137	0.91345	-159.91
5	0.98259	-177.36	0.60454	15.558	0.0051122	-62.903	0.91905	-160.68
5.2	0.98324	-177.55	0.56297	14.343	0.0048724	-63.603	0.92411	-161.41
5.4	0.98383	-177.73	0.52552	13.185	0.0046441	-64.237	0.9287	-162.09
5.6	0.98437	-177.91	0.49168	12.078	0.0044262	-64.81	0.93287	-162.73
5.8	0.98487	-178.07	0.46099	11.017	0.0042182	-65.327	0.93667	-163.34
6	0.98532	-178.23	0.4331	9.9987	0.0040191	-65.79	0.94015	-163.92

To download the s-parameters in s2p format, go to the CGHV60075D5 Product Page and click the documentation tab.

Copyright © 2014-2016 Cree, Inc. All rights reserved. The information in this document is subject to change without notice. Cree and the Cree logo are registered trademarks of Cree, Inc. Other trademarks, product and company names are the property of their respective owners and do not imply specific product and/or vendor endorsement, sponsorship or association.

Cree, Inc. 4600 Silicon Drive Durham, North Carolina, USA 27703 USA Tel: +1.919.313.5300 Fax: +1.919.869.2733 www.cree.com/rf

5 CGHV60075D5 Rev 1.1



Part Number System



Value	Units
6.0	GHz
75	W
Bare Die	-
	6.0 75

Table 1.

**Note**<sup>1</sup>: Alpha characters used in frequency code indicate a value greater than 9.9 GHz. See Table 2 for value.

Character Code	Code Value
А	0
В	1
С	2
D	3
E	4
F	5
G	6
Н	7
J	8
К	9
Examples:	1A = 10.0 GHz 2H = 27.0 GHz

Table 2.

Copyright © 2014-2016 Cree, Inc. All rights reserved. The information in this document is subject to change without notice. Cree and the Cree logo are registered trademarks of Cree, Inc. Other trademarks, product and company names are the property of their respective owners and do not imply specific product and/or vendor endorsement, sponsorship or association.

Cree, Inc. 4600 Silicon Drive Durham, North Carolina, USA 27703 USA Tel: +1.919.313.5300 Fax: +1.919.869.2733 www.cree.com/ff

# CREE ≑

### Disclaimer

Specifications are subject to change without notice. Cree, Inc. believes the information contained within this data sheet to be accurate and reliable. However, no responsibility is assumed by Cree for its use or for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Cree. Cree makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose. "Typical" parameters are the average values expected by Cree in large quantities and are provided for information purposes only. These values can and do vary in different applications, and actual performance can vary over time. All operating parameters should be validated by customer's technical experts for each application. Cree products are not designed, intended, or authorized for use as components in applications intended for surgical implant into the body or to support or sustain life, in applications in which the failure of the Cree product could result in personal injury or death, or in applications for the planning, construction, maintenance or direct operation of a nuclear facility. CREE and the CREE logo are registered trademarks of Cree, Inc.

For more information, please contact:

Cree, Inc. 4600 Silicon Drive Durham, NC 27703 www.cree.com/rf

Sarah Miller Marketing Cree, RF Components 1.919.407.5302

Ryan Baker Marketing Cree, RF Components 1.919.407.7816

Tom Dekker Sales Director Cree, RF Components 1.919.407.5639

Copyright © 2014-2016 Cree, Inc. All rights reserved. The information in this document is subject to change without notice. Cree and the Cree logo are registered trademarks of Cree, Inc. Other trademarks, product and company names are the property of their respective owners and do not imply specific product and/or vendor endorsement, sponsorship or association.

Cree, Inc. 4600 Silicon Drive Durham, North Carolina, USA 27703 USA Tel: +1.919.313.5300 Fax: +1.919.869.2733 www.cree.com/rf

7 CGHV60075D5 Rev 1.1