

# Power connectors - SACC-M12FR-4CON-PG11-M PWR - 1408991

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)

Power connectors, 4-position, Socket angled M12, A-coded, Screw connection, Knurl material: Zinc die-cast, nickel-plated, Cable gland Pg11, External cable diameter 8 mm ... 10 mm



#### Why buy this product

- Safe use in the field, thanks to a high degree of protection
- Flexible: connectors for on-site assembly
- Screw connection: proven connection technology for a large selection of different conductors



### Key Commercial Data

Packing unit	1 STK
GTIN	4 046356 885119
GTIN	4046356885119

## Technical data

#### Dimensions

External cable diameter 8 mm 10 mm
------------------------------------

#### Ambient conditions

	Degree of protection	IP67
--	----------------------	------

#### General

Note	Strip 22 mm off the cable sheath, strip 7 mm off the conductor insulation, crimp the ferrule, then shorten this to 5 mm. Length of conductor with shortened ferrule: 20 mm. Connect conductors and tighten the mounting screws with 0.2 Nm.	
Rated current at 40°C	8 A	
	when using 1.5 mm <sup>2</sup> conductors	
Rated voltage	250 V	
Number of positions	4	
Insulation resistance	> 10 GΩ	



# Power connectors - SACC-M12FR-4CON-PG11-M PWR - 1408991

# Technical data

### General

Coding	A - standard	
Standards/regulations	M12 connector IEC 61076-2-101	
Status display	No	
Overvoltage category	11	
Degree of pollution	3	
Connection method	Screw connection	
Conductor cross section 1.5 mm <sup>2</sup>		
Conductor cross section AWG 16		
nsertion/withdrawal cycles > 100		
Torque	0.4 Nm (M12 knurl)	
	1 Nm 1.4 Nm (Pressure screw with sleeve housing)	
	0.4 Nm (Screw plug insert with sleeve housing as far it will go)	
	0.2 Nm (Screw terminal blocks)	
Assembly instructions	The wires can be connected both with ferrules and without ferrules	
	The connector pin assignment can be rotated 90° to the cable outlet	

### Material

Flammability rating according to UL 94	V0
Contact material	CuZn
Contact surface material	Au
Contact carrier material	РА
Material of grip body	РА
Material, knurls	Zinc die-cast, nickel-plated
Sealing material	Viton (M12 socket)
	NBR (Cable clamping)

#### Cable

Standards/specifications	M12 connector IEC 61076-2-101		
Standards and Regulations			

		M12 connector
	Standards/regulations	IEC 61076-2-101
	Flammability rating according to UL 94	V0

## Drawings



# Power connectors - SACC-M12FR-4CON-PG11-M PWR - 1408991

#### Schematic diagram



Pin assignment M12 socket, 4-pos., A-coded, view female side



**Dimensional drawing** 

M12 x 1 socket, straight

## Approvals

Approvals

#### Approvals

UL Recognized / cUL Recognized / cULus Recognized

Ex Approvals

Γ

Г

#### Approval details

UL Recognized	http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.h	m FILE E 221474
Nominal current IN	4 A	
Nominal voltage UN	250 V	

cUL Recognized	c <b>Al</b>	http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE		FILE E 221474
Nominal current IN			4 A	
Nominal voltage UN			250 V	

cULus Recognized



http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm



Phoenix Contact 2017 © - all rights reserved http://www.phoenixcontact.com

PHOENIX CONTACT GmbH & Co. KG Flachsmarktstr. 8 32825 Blomberg Germany Tel. +49 5235 300 Fax +49 5235 3 41200 http://www.phoenixcontact.com